

Microwave Induced Instability Observed in BSCCO 2212 in a Static Magnetic Field

Y. De Wilde, H. Enriquez, N. Bontemps

Laboratoire de Physique de la Matière Condensée, Ecole Normale Supérieure, 24 rue Lhomond, 75231 Paris Cedex 05, France

T. Tamegai

Department of Applied Physics, The University of Tokyo, Hongo, Bunkyo-ku, Tokyo 113-8656, Japan

We have measured the microwave dissipation at 10 GHz through the imaginary part of the susceptibility, χ'' , in a BSCCO 2212 single crystal in an external static magnetic field H parallel to the c -axis at various fixed temperatures. The characteristics of $\chi''(H)$ exhibit a sharp step at a field H_{step} which strongly depends on the amplitude of the microwave excitation h_{ac} . The characteristics of h_{ac} vs. H_{step} , qualitatively reveal the behavior expected for the magnetic field dependence of Josephson coupling.

Vortex physics on high critical temperature superconductors (HTSC) has driven a lot of interest over the past few years¹. Because of the short coherence length which characterizes these systems, some HTSC such as BSCCO 2212, have to be described as stacks of intrinsically Josephson coupled superconducting planes², rather than as superconductors with a high effective mass anisotropy. In an externally applied magnetic field, DC transport measurements³ and thermodynamic⁴ studies have shown that melting of vortices is a first order process. In Josephson coupled HTSC's, it is still not clear if melting goes along with a total decoupling of the superconducting planes, or if instead decoupling is only achieved beyond the melting transition. Experimental studies of the Josephson plasma resonance (JPR) have been performed to investigate the temperature and magnetic field dependence of Josephson coupling⁵⁻⁸. The results point to a drop of Josephson coupling at the vortex melting^{7,8}. Other JPR experiments on BSCCO 2212 have shown the possible occurrence of nonlinear effects driven by a microwave field⁹.

We have recently presented a detailed study of melting of vortices in a BSCCO 2212 single crystal via microwave dissipation measurements¹⁰ at 10 GHz. While a careful study of vortex melting requires current densities as small as possible, and hence low microwave excitations, in this paper we focus on what happens when the amplitude of the microwave field h_{ac} is progressively increased. We observe a novel feature which shows up as a sharp step in the characteristics of dissipation vs. magnetic field at fixed temperature. In contrast with vortex melting, whose field position, H_m , only depends on the temperature, the field value at which the step occurs, H_{step} , drastically depends on h_{ac} , which we argue is closely related to the Josephson interlayer phase coherence $\langle \cos\phi \rangle$.

The experimental set-up that we use to measure the 10 GHz microwave dissipation has been described elsewhere¹¹. The sample is placed in a TE₁₀₂ resonant cavity (resonance frequency $\omega/2\pi = 9.6$ GHz) of an Electron Spin Resonance (ESR) ESP 300 E Brüker spectrometer, at the maximum of the microwave magnetic field $h_{ac}(\omega) = h_{ac} \cos \omega t$ and in zero electric field. The external static magnetic field H is applied parallel to the c -axis of the crystal, while $h_{ac}(\omega)$ is oriented within the ab -plane. The microwave field $h_{ac}(\omega)$ induces surface currents in the sample, which in this geometry flow within the ab -plane and along the c -axis. The surface currents

are responsible for an energy dissipation which is measured through the imaginary part of the susceptibility χ'' . With a small h_{ac} , in the range of a few mOe, melting of the vortex solid in BSCCO 2212 shows up as an increase of dissipation in the characteristics of χ'' vs. H recorded at a fixed temperature¹⁰.

The BSCCO 2212 single crystal used in the experiments is a rectangular platelet with dimensions $2 \times 0.8 \times 0.03$ mm³. For this sample, the critical temperature $T_c = 84$ K with a transition width $\Delta T_c \approx 0.4$ K, as measured at 10 GHz. An attenuator placed between the source and the cavity enables a step-by-step variation of the microwave power in the cavity, with an attenuation of 1dB between each step. An attenuation of 1 dB corresponds to a reduction of h_{ac} by a factor 1.12. Fig. 1 shows a typical χ'' vs. H characteristic obtained at $T = 65$ K with an input power of 0.8 mW, corresponding to $h_{ac} \approx 60$ mOe. Here melting occurs around $H_m = 315$ Oe and shows up as a small jump and a change of slope in $\chi''(H)$. There is no influence of the input power on the value of H_m measured at 10 GHz with our technique. Good agreement is found between the $H_m(T)$ phase diagram measured at 10 GHz and that obtained from DC SQUID measurements on the same sample¹⁰. The small jump in χ'' at H_m is analogous to the sharp onset of resistivity observed in DC transport measurements³. A salient new feature in Fig.1, is the sharp step which corresponds to a sudden increase of dissipation at a field $H_{step} \approx 200$ Oe. The curves shown in the inset of Fig. 1 were obtained at a temperature of 65K, with $h_{ac} \approx 47$ mOe, when sweeping the magnetic field up and down successively. A hysteretic behavior of the step is observed. The amplitude of the hysteresis loop at 65 K is of the order of 10 Oe.

Fig. 2 shows a series of characteristics of χ'' vs. H recorded at 65 K, where the input power has systematically been attenuated by 2 dB between subsequent recordings in order to vary h_{ac} . In contrast with H_m , the field H_{step} strongly depends on the input power. At 20 dB, which corresponds to $h_{ac} \approx 95$ mOe, the step occurs in the solid phase, H_{step} well below $H_m \approx 315$ Oe, and shifts to higher fields as the attenuation is increased, i.e. as h_{ac} is reduced. The step survives in the liquid phase beyond H_m , where it presents significant broadening. Similar observations of a step with 10 GHz dissipative measurements were done on other BSCCO 2212 samples, showing the intrinsic origin of the feature. On a

sample with a somewhat broader superconducting transition, the step was broader and reduced in amplitude compared to the results presented in Fig. 1 and Fig. 2. The observation of the step seems to require samples with very homogeneous superconducting properties. At high enough input power, the characteristics of χ'' vs. H exhibit an offset, indicating that the extra dissipation produced by the step *has already occurred* at $H = 0$. Other measurements of high purity BSCCO 2212 single crystals placed in a 10 GHz niobium resonator¹² in zero field showed switching of the surface resistance, probably of the same origin as the step in $\chi''(H)$ reported here.

In our geometry, $h_{ac}(\omega)$ tend to tilt slightly the field on the sample away from the c-axis of the crystal. In tilted magnetic fields, vortices in samples with a large anisotropy such as BSCCO 2212 adopt a tilted structure made of vortex pancakes linked by Josephson vortex segments^{13,14}, or may even form a two components structure with coexistent Abrikosov and Josephson vortex systems, orthogonal to each other^{15,16}. While the density of pancake vortices depends on the static field component H , the density of Josephson strings, regardless of the details of the vortex structure, is driven by the field component parallel to the superconducting CuO₂ planes, here $h_{ac}(\omega)$. The step amplitude in $\chi''(H)$ is proportional to the microwave input power and independent of the static field component. This points to a dissipation process related to Josephson strings induced by the microwave field and not to pancake vortices.

We have thoroughly investigated the temperature and power dependence of the step between 75 K and 30 K, changing the temperature by steps of 5K between each series of recordings, and the attenuation of the microwave excitation by steps of 1dB. Fig. 3 shows two series of plots of h_{ac} vs. H_{step} , which cover the entire temperature range of our studies. The arrows in these plots indicate the melting transition at H_m , whenever observed. Fig. 3 shows that h_{ac} is a decreasing function of the static field. Down to about 45 K, the characteristics of h_{ac} vs. H_{step} exhibit a fairly distinct drop which in each case coincides with the melting transition. The dependence of h_{ac} vs. magnetic field is qualitatively the same as that expected for the interlayer Josephson coupling. The additional phase difference ϕ due to the presence of pancake vortices in a perpendicular static magnetic field H produces a loss of interlayer phase coherence $\langle \cos\phi \rangle$, and so reduces the average Josephson coupling energy (or equivalently, the average Josephson current) when H increases¹⁷. Extra decoupling of the layers seems to occur at melting, producing a sudden drop of $\langle \cos\phi \rangle$. Experimental observation of this drop has been reported in the organic superconductors κ - (BEDT-TTF)₂Cu[N(CN)₂]Br and, recently, in BSCCO 2212 in measurements of the magnetic field dependence of the JPR frequency^{7,8} ω_{pl} . Note that at $T = 40$ K and below, melting could not be resolved in our measurements, neither in the characteristics of χ'' vs. H , nor via magnetization measurements with a SQUID magnetometer. Below 40 K, the drop in the characteristics of h_{ac} vs. H_{step} does not seem to be present as well in Fig. 3, in contrast with recent JPR data in which a drop in ω_{pl}^2 vs. H was still observed below the critical point⁸.

Fig. 3 shows that in the liquid phase h_{ac} can be fitted with a $1/H^\alpha$ dependence. Down to 50 K, the fits give $\alpha \approx 0.8$. Approaching 40 K, and below, α progressively increases and is of order 1.2 around 30 K. Koshelev¹⁷ has predicted that in the particular case of a vortex liquid, $\langle \cos\phi \rangle$ should exhibit a $1/H^\alpha$ dependence, with α close to unity, and be proportional to the square of the JPR frequency ω_{pl}^2 ; these predictions have been confirmed in JPR studies⁶⁻⁸. An increase of α is expected for $\langle \cos\phi \rangle$ as a consequence of disorder in the pancake arrangement along the c-axis¹⁸, due for instance to an increase of pinning at low temperature. Fig. 3 shows that the relation between h_{ac} and H found in BSCCO is very close to that expected for $\langle \cos\phi \rangle$ in the liquid phase. It suggests that h_{ac} provides a direct measure of the interlayer phase coherence, being close to proportional to $\langle \cos\phi \rangle$, in a similar way as ω_{pl}^2 . This is supported by the close similarity existing between the normalized characteristics of h_{ac} versus H_{step} , shown in Fig. 3c, and the JPR data presented in ref.⁸. Within this scenario, the fact that h_{ac} still has a substantial non zero value right beyond H_m in Fig. 3 indicates that phase coherence is not completely lost when the vortices enter the liquid phase. It is only at higher fields that vanishingly small h_{ac} 's probe almost totally decoupled layers. In the characteristics of χ'' vs. H shown in Fig. 2, the step progressively broadens in the liquid phase, suggesting that the phase difference between the superconducting layers becomes less and less homogeneous over the sample thickness as the static field is increased beyond H_m .

The step observed in Fig. 1 and Fig. 2 indicates that a new dissipation process sets in at once when H reaches a threshold value $H_{step}(h_{ac})$. When a large area Josephson junction is subject to a small in-plane magnetic field h , penetration of Josephson strings is prevented if the supercurrent density circulating at the junction periphery, over a thickness given by the London penetration depth λ_J , is smaller than the Josephson critical current density¹⁹ j_c . This defines the lower Josephson critical field $h_{c1J} \propto j_c \lambda_J$ below which h is screened. Similarly, a stacked structure of Josephson junctions such as a BSCCO single crystal should expel in-plane microwave fields of amplitude h_{ac} smaller than h_{c1J} over a length scale λ_J (generally called λ_c). An additional static field component H perpendicular to the Josephson stacks produces pancake vortices in the superconducting planes, which result in an extra loss of interlayer phase coherence and hence in a decrease of $h_{c1J}(H)$. In each characteristic of χ'' vs. H shown in Fig.1 and Fig.2, h_{ac} is kept at a constant value during the sweeps of H . Sweeping up the static field H , results in a decay of $h_{c1J}(H)$. When H is such that $h_{c1J}(H) > h_{ac}$, no microwave induced Josephson strings penetrate the sample. A further increase of H leads to the reversed situation, $h_{c1J}(H) < h_{ac}$; Josephson strings enter and leave then the sample at the microwave frequency, giving rise to an extra contribution to the dissipation. This process is expected to occur at a threshold field such that $h_{c1J}(H) = h_{ac}$, producing a step in the characteristics of χ'' vs. H like that observed experimentally at $H = H_{step}$. Hence, a possible explanation for the step could be that it is associated with the lower Josephson critical field h_{c1J} .

in BSCCO below which penetration of Josephson strings is prevented at 10 GHz.

An important consequence of this scenario is that the diagram of h_{ac} vs. H_{step} should permit to explore how Josephson coupling evolves in a static perpendicular field H , provided that the relation between h_{ac} and $\langle \cos\phi \rangle$ is known. As a first guess, we take $j_c \propto h_{ac}/\lambda_J$, which is justified at the step, since we suppose $h_{c1J}(H_{step}) = h_{ac}$ in each characteristic of χ'' vs. H . Like in ordinary Josephson junctions, we also assume¹⁹ that $\lambda_J \propto j_c^{-\frac{1}{2}} \propto \langle \cos\phi \rangle^{-\frac{1}{2}}$. Combined with the $1/H$ dependence of $\langle \cos\phi \rangle$ in the decoupled liquid phase predicted by Koshelev¹⁷, one should then expect a $1/H^{1/2}$ dependence for h_{ac} . The experimental data in Fig. 3 show instead a $1/H^\alpha$ behavior with α close to 1. On the other hand, the losses in the liquid phase should be proportional to the surface resistance $\propto \rho_{fl}/\lambda_J$, where ρ_{fl} is the flux flow resistivity which varies linearly²⁰ with H . If $\lambda_J \propto H^{\frac{1}{2}}$, the losses in the liquid phase should then exhibit a $H^{1/2}$ dependence²⁰; instead, the results presented in ref.¹⁰ show a behavior closer to linear in H . These discrepancies point to some difficulty essentially related to the field dependence of λ_J . The main reason might be the lack of knowledge about either the effective thickness λ_J^{eff} of the layer through which the microwave surface currents flow, or of its magnetic field dependence. The microwave loss data from ref.¹⁰ suggest that λ_J^{eff} weakly depends²⁰ on H , which would then be consistent with the experimentally observed $1/H$ variation of h_{ac} . More realistic models, taking into account the influence of effects such as surface defects on λ_J^{eff} might be able to reconcile the experimental observations with theory.

Recent JPR experiments of Hanaguri *et al.* on BSCCO 2212 have shown nonlinear effects induced by microwave power⁹. The nonlinearities of the JPR were qualitatively explained with the perturbed sine-Gordon equation for the Josephson phase. It predicts a lowering of the resonance frequency and the appearance of a hysteretic bistable regime at high microwave current, consistent with the experimental JPR data^{9,21}. Fig.3 shows that, at a fixed value of the static magnetic field, the step occurs at lower temperature when h_{ac} , and the associated microwave current, is increased. This behavior is similar to that observed in ref.⁹ for the nonlinear JPR. Hence, another possible interpretation for the step is that it might correspond to the switching between two stable solutions of the perturbed sine-Gordon equation. A theoretical estimate of the range of existence of each solution of the sine-Gordon equation predicts²¹ $h_{ac} \propto \langle \cos\phi \rangle^{1/2}$. This is the same analytical dependence as that predicted in the scenario involving the lower critical field h_{c1J} . It should result in a $1/H^{1/2}$ dependence of h_{ac} in the liquid phase, whereas the experimental data exhibit a behavior closer to $1/H$. A proper comparison of our data with the nonlinear JPR data⁹ and theory requires precise knowledge of the longitudinal currents which flow through the superconducting layers in both experiments. These data are not available at this stage.

In summary, the characteristics of h_{ac} vs. H_{step} , recorded at various fixed temperatures, qualitatively reveal the behavior expected for the magnetic field depen-

dence of Josephson coupling; the characteristics exhibit a drop at H_m , which points to substantial decoupling at the melting transition. We propose that the step is either related to the lower Josephson critical field h_{c1J} in BSCCO, or to nonlinear Josephson plasma resonance.

We are grateful to A. E. Koshelev for stimulating discussions. This work is supported by CREST and Grant-in-Aid for Scientific Research from the Ministry of Education, Science, Sports and Culture of Japan.

FIG. 1. Dissipation, χ'' , as a function of the applied magnetic field, H , recorded at 65 K with a microwave excitation $h_{ac} \approx 60$ mOe. The arrows indicate the step, at $H = H_{step}$, and the melting, at $H = H_{melt}$. Inset: Curves of χ'' vs. H resulting from subsequent sweeps up and down of the magnetic field H at 65 K with $h_{ac} \approx 47$ mOe showing the hysteretic behavior of the step.

FIG. 2. Series of characteristics of the dissipation χ'' versus magnetic field H recorded at 65 K with various input power. The attenuation ranges from 20 dB ($h_{ac} = 95$ mOe) to 40 dB ($h_{ac} = 9.5$ mOe).

FIG. 3. Double logarithmic plot of the amplitude of the input excitation, h_{ac} , versus the field at which the step in dissipation occurs, H_{step} , recorded (a) between 75 K and 50 K, and (b) between 50 K and 30 K. The arrows locate the melting transition, whenever observed (see text). (c) Data corresponding to $T \geq 45$ K plotted on a normalized scale, with h_{ac} and H_{step} divided by their values at melting. The dashed line corresponds to $h_{ac} \propto 1/H_{step}$.

- ¹ G. W. Crabtree and D. R. Nelson, Phys. Today **50**, 38 (1997).
- ² R. Kleiner *et al.*, Phys. Rev. Lett. **68**, 2394 (1992).
- ³ H. Safar *et al.*, Phys. Rev. Lett. **69**, 3370 (1992). D. T. Fuchs *et al.*, Phys. Rev. B **54**, R796 (1996). W. K. Kwok *et al.*, Phys. Rev. Lett. **72**, 1092 (1994).
- ⁴ E. Zeldov *et al.*, Nature **375**, 373 (1995). U. Welp *et al.*, Phys. Rev. Lett. **76**, 4809 (1996). A. Schilling *et al.*, Nature **382**, 791 (1996).
- ⁵ O. K. C. Tsui *et al.*, Phys. Rev. Lett. **73**, 724 (1993).
- ⁶ Y. Matsuda *et al.*, Phys. Rev. Lett. **78**, 1972 (1997).
- ⁷ T. Shibauchi, *et al.*, Phys. Rev. B **57**, R5622 (1998).
- ⁸ T. Shibauchi *et al.*, Phys. Rev. Lett. **83**, 1010 (1999).
- ⁹ T. Hanaguri *et al.*, Phys. Rev. B **58**, R8929 (1998).
- ¹⁰ H. Enriquez *et al.*, Phys. Rev. B **58**, R14745 (1998).
- ¹¹ H. Enriquez *et al.*, Phys. Rev. B **53**, R14757 (1996).
- ¹² T. Jacobs *et al.*, in "Physics, Materials and Applications", World Scientific, 288 (1996).
- ¹³ L. N. Bulaevskii *et al.*, Phys. Rev. B **46**, 366 (1992), and references therein.
- ¹⁴ D. Feinberg and C. Villard, Phys. Rev. Lett. **65**, 919 (1990).
- ¹⁵ M. Benkraouda and M. Ledvij, Phys. Rev. B **51**, 6123 (1995).
- ¹⁶ A. E. Koshelev, Phys. Rev. Lett. **83**, 187 (1999).
- ¹⁷ A. E. Koshelev, Phys. Rev. Lett. **77**, 3901 (1996).

¹⁸ L. N. Bulaevskii *et al.*, Phys. Rev. Lett. **76**, 1719 (1996).
¹⁹ M. Tinkham, in *Introduction to Superconductivity*, Mc
Graw Hill (1996).

²⁰ E. B. Sonin, Phys.Rev. B **60**, 15430 (1999).
²¹ A. E. Koshelev, *Private communication*.





